



ADDENDUM SHEET TO G.C.2
SERVICE MANUAL
K.B.
MODEL KG021



A DIVISION OF **STC**

Issued FEBRUARY 1965

COMBINED RADIO AND TELEVISION SERVICE LTD

REGENT WORKS, SIDCUP, KENT. Tel: FO0tscray 3333

SERVICE ORGANISATION FOR K.B. · REGENTONE · R.G.D. · ACE · ARGOSY

ALSO PROVINCIAL DEPOT AT

COLLEGE MILTON

EAST KILBRIDE

GLASGOW

EAST KILBRIDE 25101

Dimensions :

Height —	23½"
Width —	40"
Depth —	16"
Weight —	72 lbs.

DESCRIPTION	PART/LOC. No.
Cabinet	867/220/21661
Cabinet Back	867/222/21672
Back Panel (Record Changer Compartment)	867/223/21673
Knobs (Four) ...	35/311/01109
Calibrated Scale	44/44/11177
Speakers (2 off 8" x 5")	11/150/03100
Record Changer "Autoslim" (Garrard)	37/30/1/19641
P.U. Cartridge (Stereo)	GP83/2/19241
Styli LP	GP83/LP/19623
Styli Std.	GP83/78/19624
Push Button Escutcheon	35/182/13611
Plastic Window (Cabinet Back)	35/190/15365
K.B. Badge	21/117/13680
FM Plug (Black)	13/201/25275
Speaker Plug (Red)	13/201/2/25269
Speaker Plug (Brown)	13/201/1/25268
Record Changer Mains Plug (3-pin)	13/273/25285

Chassis Removal Instructions :

Pull off knobs, then remove two nuts and washers at rear of chassis. The chassis can then be removed.

Access to the underside of the Record Changer is obtained by removing the record changer compartment back cover, and releasing the transit screw retaining clips.

Cartridge loading is achieved by two 2000pF capacitors which are connected across each of the stereo outputs on the tag panel mounted on the changer.

N.B. Later versions will be fitted with a GP 81 P.U. cartridge, and the two cartridge loading capacitors changed to 470 pF, Part No. KC 87.