

CRTS

ADDENDUM SHEET TO G.C.2
SERVICE MANUAL
K.B.
MODEL WG20

A DIVISION OF **STC**

Issued FEBRUARY 1965

COMBINED RADIO AND TELEVISION SERVICE LTD

REGENT WORKS, SIDCUP, KENT. Tel: FOOTscray 3333

SERVICE ORGANISATION FOR K.B. · REGENTONE · R.G.D. · ACE · ARGOSY

ALSO PROVINCIAL DEPOT AT

COLLEGE MILTON

EAST KILBRIDE

GLASGOW

EAST KILBRIDE 25101

Dimensions :

Height —	25"
Width —	45"
Depth —	15½"
Weight —	73 lbs.

DESCRIPTION	PART/LOC. No.
Cabinet	814/220/21664
Cabinet Back	814/150/21633
Speaker Compartment Cover (Rear)	814/223/21665
Knobs (Four)	762/62/6/01666
Calibrated Scale	44/12/11301
Speakers (Two off 10" x 6")	11/123/03135
Record Changer UA15	37/24/19308
P.U. Cartridge (Stereo)	GP83/2/19241
Styli LP	GP83/LP/19623
Styli Std.	GP83/78/19624
Legs	23/47/21464
Push Button Escutcheon	35/182/13611
K.B. Badge	21/71/1/13235
K.B. Badge Escutcheon	35/69/13234
F.M. Plug (Black)	13/201/25275
Speaker Plug (Red)	13/201/2/25269
Speaker Plug (Brown)	13/201/1/25268
Record Changer Mains Plug (3-pin)	13/273/25285

Chassis Removal Instructions :

Pull off knobs, then remove two 4BA screws at rear of chassis and the screws through the brackets on either side of the chassis (near the front). The chassis can then be withdrawn.

Access to the underside of the Record Changer is obtained by removing the motor board which is secured by six screws.

Cartridge loading is achieved by two 500pF capacitors which are connected across each of the stereo outputs on the tag panel mounted on the changer.

N.B. Later versions will be fitted with a GP 81 P.U. cartridge, and the two cartridge loading capacitors deleted.