

**CRTS****ADDENDUM SHEET TO G.C.6****SERVICE MANUAL****Regentone****TG439**A DIVISION OF **STC**

Issued February, 1966

**COMBINED RADIO AND TELEVISION SERVICE LTD**

REGENT WORKS, SIDCUP, KENT. Tel: FOOtscray 3333

SERVICING ORGANISATION FOR K.B. REGENTONE, R.G.D. ACE, ARGOSY.

ALSO SCOTTISH DEPOT AT

COLLEGE MILTON

EAST KILBRIDE

GLASGOW

EAST KILBRIDE 25101

**Dimensions :**

Height —	17½"
Width —	36"
Depth —	14"
Weight —	31¼ lb.

**PARTS LIST FOR TG439**

DESCRIPTION	PART/LOCATION No.
Cabinet	1185/220/211008
Cabinet Bottom	34/140/27361
Lid Stay, 3½" Bronze	1185/220/56/211085
Knobs, 4 off	35/183/01686
Calibrated Scale	44/54/1/11376
Speaker (8" x 5", Impedance 15 ohms)	11/174/03154
Record Changer BSR UA15	37/33/19652
Record Changer Motor	37/33/M/19621
P.U. Cartridge TC8M	TC8M/19257
Stylus L.P.	TC8R/19232
Stylus 78	TC8G/19240
Aerial Lever	33/408/201065

**Chassis Removal Instructions**

Remove cabinet bottom and disconnect motor supply and H.T. feed from terminal block. Unsolder S.W. aerial and disconnect speaker and P.U. leads from their respective tag panels. Unscrew the mains cable cleat, pull off knobs and remove the 3 4BA nuts holding the chassis to the cabinet and remove chassis.

Access to the underside of the record changer is obtained by removing the cabinet bottom and releasing the transit screw retaining clips.